

1. SOT-23 SWITCHING DIODES

(Package): SOT-23



TYPE	V(BR)R V _{dc}		I _F mA	V _F V _{dc}			I _R		t _{rr} ns	STYLE
	Min V _{dc}	I _R μ A		Min	Max V	I _F mA	Max μ A	VR V		
BAL99LT1	70	100	100		1.0	50	2.5	70	6.0	18
BAS16LT1	75	100	200		1.25	150	1.0	75	6.0	8
BAS21LT1	250	100	200		1.25	200	0.1	200	50	8
BAS116LT1	75	100	200		1.25	150	5.0nA	75	3.0μS	8
BAV70LT1	>70	100	200		1.25	150	2.5	70	6.0	9
BAV74LT1	50	5.0	200		1.0	100	0.1	50	4.0	9
BAV99LT1	70	100	215		1.25	150	2.5	70	6.0	11
BAV170LT1	70	100	200		1.25	150	5.0	70	3.0μS	9
BAV199LT1	70	100	215		1.25	150	5.0	70	3.0μS	11
BAW56LT1	70	100	200		1.25	150	2.5	70	6.0	12
BAW156LT1	70	100	200		1.25	150	5.0	70	3.0μS	12
MMBD101LT1	7.0	10			0.6	10	0.25	3.0		8
MMBD301LT1	30	10			0.45	1.0	200nA	25		8
MMBD701LT1	70	10			0.5	1.0	200nA	35		8
MMBD352LT1	7.0				0.60	10	10	7.0		11
MMBD353LT1	7.0				0.60	10	10	7.0		19
MMBD354LT1	7.0				0.6	10	10	7.0		9
MMBD914LT1	100	100	200		1.0	10	5.0	75	4.0	8
MMBD2835LT1	35	100	100		1.2	100	100nA	30	4.0	12
MMBD2836LT1	75	100	100		1.2	100	100nA	50	4.0	12
MMBD2837LT1	35	100	IFM450		1.2	100	0.1	30	4.0	9
MMBD2838LT1	75	100	IFM450		1.2	100	0.1	50	4.0	9
MMBD6050LT1	70	100	200		1.1	100	0.1	50	4.0	8
MMBD6100LT1	70	100	200		1.1	100	0.1	50	4.0	9
MMBD7000LT1	100	100	200		1.1	100	3.0	100	4.0	11